



Spannungskonstante LED Multi Konverter mit 1-10V Dimmung

- Flickerfrei.
- Konstantstrom wählbar
- mit Überlastungsschutz
- mit Überspannungsschutz
- mit Überhitzungsschutz
- mit Kurzschluss-Schutz

| | | | | |
|--------------------|---|--|------------|----------------|
| 20W 350...900mA | Konstantstrom 13W 20...53V 250mA 15W 20...52V 300mA 18W 15...50V 350mA 20W 15...50V 400mA 20W 5...45V 450mA 20W 5...40V 500mA 20W 3...37V 550mA 20W 3...34V 600mA 20W 3...31V 650mA 20W 3...29V 700mA 20W 3...27V 750mA 20W 3...25V 800mA 20W 3...24V 850mA 20W 3...23V 900mA | Konstantspannung 11W 12V max. 900mA 20W 12V max. 900mA | TCI-125400 | 54,13 € |
|--------------------|---|--|------------|----------------|



L x B x H 11,1 x 5,2 x 2,2 cm

| | | | | |
|--------------------|---|--|------------|----------------|
| 32W 250...900mA | Konstantstrom 13W 15...53V 250mA 16W 15...53V 300mA 18W 10...53V 350mA 21W 10...53V 400mA 23W 5...52V 450mA 25W 2...50V 500mA 27W 2...50V 550mA 30W 2...50V 600mA 32W 2...49V 650mA 32W 2...46V 700mA 20W 2...43V 750mA 20W 2...40V 800mA 20W 2...39V 850mA 20W 2...37V 900mA | Konstantspannung 11W 12V max. 900mA 20W 24V max. 830mA | TCI-125421 | 61,51 € |
|--------------------|---|--|------------|----------------|



L x B x H 10,3 x 6,7 x 2,1 cm

| | | | | |
|-----------|---|-----------------------|------------|----------------|
| 38W 1-10V | Konstantstrom 16W 10...54V 300mA 18W 10...54V 350mA 21W 10...54V 400mA 24W 10...54V 450mA 27W 10...54V 500mA 29W 10...54V 550mA 32W 10...54V 600mA 35W 10...54V 650mA 36W 10...51V 700mA 36W 10...48V 750mA 36W 10...45V 800mA 36W 10...42V 850mA 36W 10...40V 900mA 36W 10...38V 950mA 36W 10...36V 1000mA 36W 10...35V 1050mA | Konstantspannung k.A. | TCI-127496 | 71,20 € |
|-----------|---|-----------------------|------------|----------------|



L x B x H 14,7 x 4,4 x 3 cm