



DEKO-LIGHT RF-SMART STARTER-SET 1 230V TRIAC DIMMER + RF-REMOTE CONTROL

- Dimmable brightness
- Intelli-Push dim function (on/off, brightness) via potential-free push-button
- can be controlled with all RF smart wireless remote controls (2.4 GHz, range approx. 30 m)
- can be controlled with all Zigbee 3.0 compatible controls/apps such as Amazon Echo (Alexa), Google Assistant, Tuya (relevant gateway required, outdoor range up to 100 m)
- Program and remote control synchronisation when operating multiple RF smart components (repeater function)
- Control of 230 V (R/C) components
- Minimum brightness adjustable in ten steps
- Switch mode adjustable (dimming disabled)
- up to 10x LED-LM/7x LED ballast units can be connected (max. 300 W for R/C loads)
- One control zone
- Remote control operated with 2x AAA batteries (not included in the scope of delivery)
- Set comprises: 1x 843503 + 1x 843508

Housing	Plastic	Rated Input Voltage	100-240 V/AC
Length	25 mm	Control	RF-Smart, Trailing-edge dimmer, ZigBee 3.0, Intelli Push-Dim
Width	70 mm		
Height	70 mm		
Power	1.0-300 W	Channels	1
Output Current	1.36 A		

Article Price

843500 **€ 99.95**

