





DEKO-LIGHT RF-SMART TRIAC DIMMER 230 V

- ·Dimmable brightness
- •Programme and remote control synchronisation when operating multiple RF-smart components (repeater function)
- ·Intelli-Push dimming function via potential-free push-button
- •Can be controlled with RF-smart wireless remote controls (2.4 GHz, range approx. 30 m, not included in the scope of delivery)
- •Can be controlled with all Zigbee 3.0 compatible controllers/apps such as Amazon Echo (Alexa), Google Assistant, Tuya (relevant gateway required, outdoor range up to 100 m)
- ·For controlling 230 V components
- ·Minimum brightness adjustable in ten stages
- ·Up to 10x LED lamps/7x ballasts can be connected (max. 300 W for R/C loads)
- ·Adjustable switch mode (dimming disabled)

| Output Current | 1.36 A | Rated Input Voltage | 100-240 V/AC |
|----------------|-----------|---------------------|---------------------------------|
| Housing | Plastic | Control | RF-Smart, Trai- |
| Length | 25 mm | | ling-edge dimmer, |
| Width | 49 mm | | ZigBee 3.0, Intelli Push-Dim |
| Height | 49 mm | Channels | 1 |
| Power | 1.0-300 W | | |

