







DEKO-LIGHT RF-SMART OUTDOOR TRIAC-DIMMER 230V

- ·Dimmable brightness
- ·Intelli-Push dim function (on/off, brightness) via potential-free push-button
- ·can be controlled with RF smart wireless remote controls (2.4 Ghz, range approx. 30 m, not included in the scope of delivery)
- ·can be controlled with all Zigbee 3.0 compatible controls/apps such as Amazon Echo (Alexa), Google Assistant, Tuya (relevant gateway required, outdoor range up to 100 m)
- ·Program and remote control synchronisation when operating multiple RF smart components (repeater function)
- ·Control of 230 V components
- ·Minimum brightness adjustable in ten steps
- ·Switch mode adjustable (dimming disabled, additional load relays can be connected)
- ·up to 10x LED-LM/7x LED ballast units can be connected (max. 300 W for R/C loads)
- Outdoor distribution board IP67 with up to four cable entry points from 4-14 mm as well as two blanking plugs

| Output Current | 1.36 A | Rated Input Voltage | 100-240 V/AC |
|----------------|---------|---------------------|---------------------------------|
| Housing | Plastic | Control | RF-Smart, Trai- |
| Length | 170 mm | | ling-edge dimmer, |
| Width | 155 mm | | ZigBee 3.0, Intelli Push-Dim |
| Height | 65 mm | | 4 |
| 5 | | Channels | I |

Article Price







Power







1.0-300 W